

09/93/918

Description

Method for transferring data streams, having different data transmission rates, between a first and second data transmission unit

In order to utilize better the transmission capacity available in communications networks, in particular optical communications networks, multiplexers are used to multiplex input-end channels in wavelength multiplexers. These multiplexers make it possible, on the one hand, to make better use of the bandwidth of the optical channels and, on the other hand, to reduce the number of selective lasers necessary for wavelength multiplexing.

Contemporary multiplexers, in particular multiplexers used in SONET/SDH data transmission are costly and very complex. Such multiplexers have the disadvantage that they only permit data streams or SDH data signals which are configured in accordance with the synchronous digital hierarchy SDH to be multiplexed, the multiplexers being configured in accordance with the ITU Recommendation G.707.

The invention is based on the object of achieving maximum or effective use of the transmission capacity made available by the communications network when a plurality of data streams having different data transmission rates are transmitted over a communications network, in particular over an optical communications network. The object is achieved by means of a method based on a method according to patent claim 1, by means of its characterizing features.

The central aspect of the method according to the invention for transferring data streams, having

09937918-100101

different transmission rates, between a first and second data transmission unit is that the

05937918.100101

data streams to be transferred are inserted into data frames each having the same data volume and the same data transmission rate.

- 5 The essential advantage of the method according to the invention is that it is possible to implement a transparent transmission of data streams having any desired data transmission rates, or a transparent transmission of information which is transferred using
10 any desired data transmission method and has any desired data formats. Furthermore, optimum, i.e. maximum use of the transmission capacity made available by a communications network and/or optimum use of the bandwidth of a data transmission channel made available
15 for transferring information is achieved. By using a uniform data frame it is possible to dispense with complex pointer methods in multiplexers. Moreover, it is possible to reduce the number of selective lasers at the input of wavelength multiplexers which make
20 available a data transmission channel.

- According to one advantageous refinement of the method according to the invention, the data transmission rate of the data frames is adapted to the data transmission
25 rates of the data streams using stuffing information which is respectively arranged in the data frames - claim 3. As a result of this advantageous refinement, the data transmission rates of the data streams inserted into the data frames can have small,
30 acceptable fluctuations.

- Further advantageous refinements of the method according to the invention and a use of the method according to the invention can be found in the further claims.

35

The method according to the invention will be explained in more detail below with reference to a plurality of drawings, in which:

05937918 "100101

FIG 1 shows a detail of a data transmission path,
FIG 2 shows a data frame for multiplexing a
2.666057 Gbps data stream,
FIG 3 shows a data frame for multiplexing a
2.488320 Gbps data stream,
FIG 4 shows a data frame for multiplexing 1.250 Gbps
data streams,
FIG 5 shows a multiplex structure for forming the
multiplex signal,
FIG 6 shows a data frame for a multiplex signal.

FIG 1 shows a detail from a data transmission system in
which wavelength multiplexers are arranged for, for
example, N x 10 Gbps channels. In the data transmission
5 system illustrated, a first data transmission unit
representing a terminal multiplexer MUXE is arranged,
by means of which data signals or data streams e1, e2,
e31, e32 which are present at inputs EM1...4 and have
different data transmission rates are combined.

10 For this exemplary embodiment it will be assumed that a
data signal e1 having a data transmission rate of
2.666057 Gbps or a data stream e1 having a data
transmission rate of 2.666057 Gbps is fed to the first
15 input EM1 of the multiplexer MUXE. This data signal or
data stream is specified by the ITU-T in the
Recommendation G.975 and describes an STM-16/OC-48
signal with FEC (Forward Error Correction). A
2.488320 Gbps data signal e2 or a data stream e2 having
20 a transmission rate of 2.488320 Gbps is fed to the
second input EM2 of the multiplexer MUXE. This data
signal e2 is specified by the ITU-T in the
Recommendation G.707 and describes an STM-16/OC-48
signal. Furthermore, in each case a 1.250 Gbps data
25 signal or in each case a data stream e31, e32 having a
data transmission rate of 1.250 Gbps is fed to the
third and fourth inputs of the multiplexer MUXE.

05937918-100101

This data signal e31, e32 is specified by IEEE P802.3 and describes a data signal referred to as "Gigabit-Ethernet".

5 The output signal which is present at the output AM of the terminal multiplexer MUXE is passed on to a wavelength multiplexer WDM. The data which is directed via a wavelength multiplexer WDM is transmitted, for example, via optical or electric amplifiers OA, ER and
10 further wavelength multiplexers WDM, to a data transmission unit which is arranged at the end of the data transmission system and also represents a terminal multiplexer MUXA.

15 The data signals or data streams e1, e2, e31, e32 which are present at the four inputs EM1...4 are each inserted into data frames - also referred to as containers - DR1...3 using a frame forming unit (not illustrated) which is arranged in the multiplexer MUXE, the data
20 frames DR1...3 each having the same data volume and the same data transmission rate. The data frames DR1...3 which are formed and the data signals e1, e2, e31, e32 which are inserted into the data frames DR1...3 are subsequently multiplexed by the multiplexer MUXE and
25 converted into a multiplex signal a which represents the output signal.

FIG 2 illustrates a first data frame DR1 for multiplexing the 2.666057 Gbps data signal e1 - STM-16/OC-48 with FEC. The 2.666 Gbps data signals e1 which are specified in accordance with the Recommendation G.975 can be plesiochronous with respect to one another and when they are they can have a maximum deviation from the setpoint frequency of 4.6 ppm - parts per million. The first data frame DR1 has 6 subframes UR1...6. In the first subframe UR1, 225 data bits of the 2.666 Gbps data signal e1 are transmitted as user data. A first and second stuffing check bit C1, C2 are

arranged in each case at the start of the second to sixth subframes UR2...6. In the sixth subframe UR6,

09937918 .100101

a first and second stuffing bit S1, S2 are additionally arranged following the two stuffing check bits C1, C2. 225 data bits are transmitted in each of the second to fifth subframes UR2...5 following the two stuffing check bits C1, C2, and 223 data bits of the 2.66 Gbps data signal e1 are transmitted as user data nd in the sixth subframe UR6 following the two stuffing check bits C1, C2 and the two stuffing bits S1, S2.

10 The first data frame DR1 has in total a data volume of 1360 bits, of which, depending on the status or use of the two stuffing bits S1, S2, 1348 to 1350 bits can be used for transferring data bits of the 2.666 Gbps data signal e1 as user data nd. In order to permit the data signal e1 present at the first input EM1 of the multiplexer MUX to be multiplexed, a stuffing method is used. For example, a positive stuffing method can be used. In this stuffing method, the stuffing information is transmitted in the first and second stuffing check bits C1, C2, the first and second stuffing check bits C1, C2 each indicating whether or not the two stuffing bits S1, S2 are filled with user information. For example, if the bit combination "00000" is assigned to the first stuffing check bits C1, this indicates that the first stuffing bit S1 is used to transfer data bits of the data signal e1. If the bit combination "11111" is assigned to the first stuffing check bits C1, this indicates that the first stuffing bit S1 is a stuffing bit. In order to protect against individual bit errors in the stuffing check bits C1, C2 arranged in the first data frame DR1, a majority decision is advantageously carried out.

Depending on the use or status of the two stuffing bits S1, S2 arranged in the first data frame DR1, 1348 to 1350 data bits of the first data signal e1 are transmitted as user data nd by the first data frame DR1. When a positive stuffing method is used, the data

00037513 "100101

transmission rate of the first data frame DR1 is
selected such that in the nominal case,

09037918-100101
FOI001-2162E560

1349 user data bits nd are transmitted per data frame. This leads to a nominal bit rate of the first data frame DR1 of

5 $2.666057 \text{ Gbps} \times 1360 \text{ bits} / 1349 \text{ bits} =$
2.687796 Gbps.

The stuffing method used thus permits fluctuation of the data transmission rate of the data signal e1 inserted into the first data frame DR1 within the following limits f_o , f_u :

15 $f_o = 2.687796 \text{ Gbps} \times 1350 \text{ bits} / 1360 \text{ bits} =$
2.668032 Gbps

15 $f_u = 2.687796 \text{ Gbps} \times 1348 \text{ bits} / 1360 \text{ bits} =$
2.664080 Gbps.

20 The derived limits f_o , f_u of the data transmission rate of the first data signal e1 correspond to an acceptable deviation of $2.668032 / 2.666057 = 1.000741$, which corresponds to an acceptable deviation of 741 ppm. This is higher than the maximum frequency deviation of a transmission signal of 4.6 ppm which is permitted in accordance with ITU Recommendation G.813, page 3, chapter 5.

30 FIG 3 illustrates a second data frame DR2 for multiplexing the 2.488320 Gbps data signal e2. For the second data frame DR2 which also has six subframes UR1...6, the same stuffing method as in the first data frame DR1 is used. In contrast to the first data frame DR1 illustrated in FIG 2, in the case of the second data frame DR2 fifteen times fourteen data bits 14D of the second data signal e2 as user data followed by a fixed stuffing bit R are alternately transmitted in the user data field nd of each of the first to fifth subframes UR1...5. In the

05937918-100101

sixth subframe UR6 of the second data frame DR2,
12 data bits 12D of the second data signal e2 are
transmitted as user data followed by a fixed stuffing
bit R, and subsequently fourteen times fourteen data
5 bits 14D of the second data signal e2 as user data
followed by a fixed stuffing bit R are alternately
transmitted in each case.

09937918.100101

FIG 4 illustrates the third data frame DR3 for the simultaneous multiplexing of two 1.250 Gbps data signals e31, e32, which are also referred to as Gigabit-Ethernet data signals according to IEEE P802.3.

The third data frame DR3 also has six subframes UR1...6, a first and second stuffing check bit C1, C2 being arranged at the start of each of the second to sixth subframes UR2...6. In addition, a first and second stuffing bit S1, S2 are arranged in the sixth subframe UR6, following the two stuffing check bits C1, C2. The data bits of the two 1.250 Gbps data signals e31, e32 to be transferred are inserted into the subframes UR1...6

after alternate or bit interleaving, i.e. the six subframes UR1...6 in each case alternately transfer one bit of the first Gigabit-Ethernet signal e31 and one bit of the second Gigabit-Ethernet signal e32. The

5 first stuffing check

09037918 "100101

090376-100101

frame DR3 to fluctuate within the following limits f_o ,
 f_u :

00037518 " 100101

$$f_o = 2.687796 \text{ Gbps} \times 633 \text{ bits}/1360 \text{ bits} = 1.251011 \text{ Gbps}$$

$$f_u = 2.687796 \text{ Gbps} \times 632 \text{ bits}/1360 \text{ bits} = 1.249035 \text{ Gbps}$$

The derived limits f_o , f_u the data transmission rates of the two Gigabit-Ethernet signals e31, e32 correspond to an acceptable deviation of $1.250/1.249035 = 1.000772$, which corresponds to an acceptable deviation of 772 ppm.

FIG 5 illustrates in a self-explanatory fashion a multiplex structure for forming a multiplex signal. By way of example it will be assumed that in each case four frame signals each representing one of the data frames DR1...3 are multiplexed in any desired combination to form a multiplex signal as. According to FIG 5, the four input signals e1, e2, e31, e32 are inserted into the corresponding data frames DR1...3 as a function of their data transmission rate, the data transmission rates of the inserted data signals e1, e2, e31, e32 being adapted to the uniform data transmission rate of the data frames DR1...3 by inserting fixed stuffing bits and by means of the stuffing method described. The data frames DR1...3 formed are then bit interleaved using multiplex means AUG. In a following frame forming unit STM - for example a "synchronous transport module" STM - a frame alignment word RKW and corresponding overhead information OU are added to the interleaved data signal or data stream and the multiplex signal as is formed therefrom.

The multiplex signal as which is formed is subsequently transferred via the communications network to the destination multiplexer MUXA which is illustrated in FIG 1 and in which the received multiplex signal as is

00037918 "100101

demultiplexed again into the data frames DR1...3 or into the data signals e1, e2, e31, e32 inserted therein.

FIG. 6 illustrates an exemplary refinement of the
5 multiplex signal as formed. At the start of the multiplex

00937918-100101

signal as, the frame alignment word RKW, which has a data volume of 16 bits, is arranged. The overhead information OH having a data volume of 8 bits is arranged following the frame alignment word RKW. The multiplex signal as illustrated is also subdivided into six subframes UR1...6, the six subframes having in total a data volume of 5464 bits. The data bits of any desired combination of four data frames DR1...3 which are formed are inserted after bit interleaving into the six subframes UR1...6. By means of the bit interleaving of any respective desired combination of four data frames DR1...3 which are formed, the respective subframes UR1...6 of the four data frames C1...4 are correspondingly combined or multiplexed, for example the respective first subframes UR1 of the four data frames DR1...3 which are combined in the multiplex signal as are arranged in bit-interleaved form in the first subframe UR1 of the multiplex signal as. The first and second stuffing check bits C1, 2 which are arranged in each of the second to sixth subframes UR2...6 of the multiplexed data frames DR1...3 are arranged at the start of each of the second to sixth subframes UR1...6 of the multiplex signal as, and the first and second stuffing bits S1,2 of the multiplexed data frames DR1...3 are correspondingly subsequently arranged in the sixth subframe UR6 of the multiplex signal.

The data transmission rate of the multiplex signal as is obtained as:

$$f_m = 2.687796 \text{ Gbps} \times 5464/1360 = 10.798616 \text{ Gbps}$$

It is to be noted that any desired data frames DR1...3 with any desired data volume and data transmission rates can be formed using the method according to the invention, the data frames DR1...3 being multiplexed to form any desired multiplex signals as. As

00937918 "100101

a result, optimum input signals which are adapted to the transmission channels of the wavelength multiplexers can be provided for the wavelength multiplexers. For example,

SECRET

according to one refinement variant (not illustrated)
eight of the input signals e1, e2, e31, e32 described
are fed to the multiplexer MUXE, the input signals e1,
e2, e31, e32 which are fed in being multiplexed to form
5 a 20 Gbps multiplex signal as.

09037918.100101